

Q1

Q1

a)

112	0
56	0
28	0
14	0
7	1
3	1
1	1
0	1

$$112_{10} = 1110000 \text{ Binary}$$

$$= \underbrace{0111}_7 \underbrace{0000}_0 = 70 \text{ Hexadecimal}$$

b) $12_{10} - 18_{10} = A = 01100 \quad B = 010010$

$$-B = 101101 + 1$$

$$= 101110 \quad 2' \text{ Complement of } B$$

$$A - B = \begin{array}{r} 01100 \\ + 101110 \\ \hline 111010 \end{array}$$

$$A - B \text{ number} = 000110_2 = -6$$

Q2

Q2

a) $F(a, b, c, d) = (\bar{a}b + ac + bc) + ab(\bar{a}\bar{c}\bar{d} + c\bar{b}\bar{d})$

$$= [\bar{a}b + ac + bc(a + \bar{a})] + (0 + 0)$$

$$= \bar{a}b + \bar{a}c + a\bar{b}c + \bar{a}bc = \bar{a}b + ac$$

b) $F(a, b, c, d) = (\bar{a}b \oplus c\bar{d}) + a \text{ from diagram}$

$$= (\bar{a}b \cdot c\bar{d}) + \bar{a}b \cdot \bar{c}\bar{d} + a$$

$$= [ab(\bar{c} + \bar{d}) + (\bar{a} + \bar{b})cd] + a$$

$$= ab\bar{c} + ab\bar{d} + \bar{a}cd + \bar{b}cd + a$$

$$= \bar{a}cd + \bar{b}cd + a$$

$$= cd + \bar{b}cd + a = cd + a$$



Before minimization Delay = Delay_{NAND} + Delay_{AND} + Delay_{OR}

$$= 15 + 20 + 15 = 50 \text{ ns}$$

After minimization Delay = Delay_{NAND} + Delay_{OR}

$$= 10 + 15 = 25 \text{ ns}$$

Q3

Q3

d)

0	1	4	X	12	X	8	1
1		5	1	13	X	9	
3	1	7		15	1	11	X
2	X	6	X	14	X	10	X

$$PI1 = \sum m(0, 2, 4, 6, 8, 10, 12, 14) = \bar{d} \text{ Essential}$$

$$PI2 = \sum m(2, 3, 10, 11) = \bar{b}c \text{ Essential}$$

$$PI3 = \sum m(4, 5, 12, 13) = b\bar{c} \text{ Essential}$$

$$PI4 = \sum m(12, 13, 14, 15) = ab$$

$$PI5 = \sum m(10, 11, 14, 15) = ac$$

$$F(a, b, c, d) = PI1 + PI2 + PI3 + \begin{cases} PI4 \\ PI5 \end{cases} \text{ either can be selected}$$

$$= \bar{d} + \bar{b}c + b\bar{c} + \begin{cases} ab \\ ac \end{cases}$$

$$b) F(A, B, C, D) = (A + CD)B \\ = (A + C)(A + D)B$$

$$c) F(A, B, C) = BC + A(B + C) \\ = BC + AB + AC$$


$$PI1 = \prod M(0, 1) = (A + B)$$

$$PI2 = \prod M(0, 2) = (A + C)$$

$$PI3 = \prod M(0, 4) = (B + C)$$

$$F = (A + B)(A + C)(B + C)$$

AB	00	01	11	10
0	0	0	1	0
1	0	1	1	1



Q4

Q4

